



JETEXINDIA

# CONTACTCLEAN-L

## Efficient Cleaner

### Technical Data Sheet

## Non Flammable, On Line, Electrical Contact Cleaner

### Description

CONTACTCLEAN-L is a non-flammable blend of high purity cleaners designed to clean electrical contacts and switches. Formulated specially for use on sophisticated equipment, this fast drying contact cleaner is non-conductive, does not leave any residue and is non-toxic. It has a very low surface tension and quickly penetrates minute crevices, cracks or pores to clean the surfaces and safely rinses off light oils, dust, fingerprints, silicones, oxides, carbon or moisture. Premium is safe to use on most plastics, metals, rubbers, elastomers & other insulating material and does not contain any CFC's, chlorinated solvents or any ozone depleting chemicals. Formulated with non flammable, safe, CO<sub>2</sub> propellant

### Benefits

- Fast penetrating and rapidly evaporating non-flammable high purity cleaner suitable for 'on-line' cleaning applications
- Low surface tension and superior wetting abilities ensure effective cleaning
- Cleans equipment fast and leaves no residue or oily films
- Non staining & non corrosive
- Non conductive
- Lowers electrical resistance at contact points
- Quickly dislodges oil, grease, silicones, fingerprints, carbon, oxides and other light contaminants from precision electrical / electronic equipment
- Extends wear life of the equipment and reliability of performance
- High dielectric strength
- Prevents intermittent failure of equipment, arcing, tracking, short circuits and corona discharges
- Safe on most plastics, metals, rubbers, insulation materials
- 360° valve allows product to be sprayed in any position - even inverted

### Available Packaging

- 500 g / 400 ml aerosol

### Shelf Life

12 months from date of manufacture in sealed condition.

### Applications

Contacts, controls, relays, PCB's, switches, motors, connectors, generators, ignition systems, terminals, sensors, circuit breakers, plugs & sockets, fuse boxes, transformers, switch gears, bearings, generators, gears, tuners, bush bars, connectors, potentiometers, solenoids, capacitors, communication equipment, oxygen systems, electrical equipment, electronic equipment, aviation equipment, industrial equipment

### Directions For Use

Spray liberally on the surface to be cleaned till the cleaning agent runs off as clear. Use extension tube for hard to reach areas. Use an abrasive or brush to clean heavy oxides or other deposits. Spray starting at the top and finishing at the bottom. Test on plastics by using on a small area before use.

### JETEX INDUSTRIES

Registered Office: 101, MALWA, PATANWALA INDL. ESTATE, LBS MARG, GHATKOPAR (W), MUMBAI-400086, INDIA.

[www.jetexindia.com](http://www.jetexindia.com)



# CONTACLEAN-L

**Non Flammable, On Line,  
Electrical Contact Cleaner**

**Technical Data Sheet**

---

## Technical Properties\*

---

Type	Cleaner
Appearance	Liquid
Color	Clear
Odor	Mild ether like
Specific Gravity @ 20°C	Above 1.20 gm/cc
Flash Point	None
Boiling Point	32°C
Solubility	Nil in water
Vapor Density	>air
Percent Volatile	100
Evaporation Rate	Very fast
Dielectric Strength	>30 kV
Kauri Butanol Value (KB)	56
Propellant	CO <sub>2</sub>
Shelf Life	1 year

\* of active ingredients